

VISTA-120 CONTROL PANEL



The VISTA-120 is an advanced, powerful system. It supports 8 partitions, while at the same time uses 4 wired, multiplex and wireless zones (up to 128 zones). In addition, powerful output control through relays can activate appliances and CCTV.

Zone Characteristics

- 9 basic 4-wired zones standard 3 panic keypads, duress
- The 9th zone at 10ms or 350ms can be set
- Expandable to 128 zones by wireless or multiplex polling

Control Specifications

- 8 partitions or 3 common areas partitions, can be used as 8 independent control panels
- Selectable for 4146 locks or wireless keyfob
- Support 4286 VIP telephone module to control through phone system
- 224 event memory log, remote downloading or check from keypad directly
- Support 7 levels 150 user codes
- Set Exit/Entry or zones around siren alert
- When use to set STAY or quick setting, automatically set aside non-functioned zones
- Integrated audio or video alarm verification options

Output Features

- Built-in dialer, automatically sending alert when alarm signal received
- RS232

Electrical

- 7AH Rechargeable back-up battery, 12VDC
- 16.5VAC, 25VA adapter

Output Specifications

- Alarm current: 2Amps, 12VDC
- 750mA auxiliary 12VDC current
- Support 96 relays max.

Honeywell

* Due to continuous product enhancement, Sin Chew Alarm reserves the right to change / modify specification without prior notice.